

Virtual Synchronous Machine Grid-Forming Inverter Model Specification (REGFM_B1)

Contributors:

Wei Du	Pacific Northwest National Laboratory		
Sebastian Achilles	General Electric		
Deepak Ramasubramanian	Electric Power Research Institute		
Philip Hart	General Electric		
Shruti Rao	General Electric		
Wenzong Wang	Electric Power Research Institute		
Quan Nguyen	Pacific Northwest National Laboratory		
Jinho Kim	Pacific Northwest National Laboratory		
Qian Zhang	Electric Power Research Institute		
Hanchao Liu	General Electric		
Pedro Arsuaga Santos	General Electric		
James Weber	PowerWorld		
Juan Sanchez	General Electric		
Mengxi Chen	General Electric		
Jayapalan Senthil	Siemens PTI		
Pouyan Pourbeik	Power and Energy, Analysis, Consulting		
	and Education (PEACE) PLLC		
Udoka Nwaneto	Pacific Northwest National Laboratory		
Jeff Bloemink	PowerTech Labs		
Song Wang	Portland General Electric		
Doug Tucker	Western Electricity Coordinating Council		
Songzhe Zhu	GridBright		



DISCLAIMER

This report was prepared as an account of work sponsored by an agency of the United States Government. Neither the United States Government nor any agency thereof, nor any of their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or usefulness of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by trade name, trademark, manufacturer, or otherwise does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency thereof. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency thereof.

Technical Report (Arial 10 pt Bold) Publication Number Month Year (Arial 10 pt)

Acknowledgments

This material is based upon work supported by the U.S. Department of Energy's Office of Energy Efficiency and Renewable Energy (EERE) under the Solar Energy Technologies Office Award Number 38637. We would also like to acknowledge the Western Electricity Coordinating Council (WECC) Modeling and Validation Subcommittee (MVS) for supporting this model development work.

1 Introduction

This report describes a generic virtual synchronous machine (VSM) grid-forming inverter (GFM) model—REGFM_B1. The initial model specification was proposed by Pacific Northwest National Laboratory (PNNL), General Electric (GE), and Electric Power Research Institute (EPRI). Siemens Gamesa Renewable Energy (SGRE) also provided inputs to the specification. The model specification has been revised multiple times based on the discussions between all the contributors listed in this report. This work was funded by the Universal Interoperability for Grid-Forming Inverters (UNIFI) Consortium.

This generic model is developed to help the utility industry understand the concept of VSM GFMs. The model could be used to represent equipment for long-term planning studies where vendor-specific models are not available. As equipment mature and improve, generic models will be updated to capture the new functionalities of GFMs. It is not intended that these models will always remain representative of all future GFM technologies.

2 VSM GFM Model (REGFM_B1)

The main circuit of a VSM GFM can be represented as a voltage source behind impedance as shown in Figure 1.



Figure 1 Voltage source representation of a grid-forming inverter

Figure 2 shows the virtual synchronous machine control block. In (1) and (2), P and I_d are per unit values on the system base, and P_{inv} and I_{dinv} are per unit values on the inverter rating base.



Figure 2 Virtual synchronous machine control

$$P_{inv} = \frac{1}{1 + T_{Pf}s} P \frac{S_{base}}{M_{base}}$$
(1)

$$I_{dinv} = \frac{1}{1 + T_{lf} S} I_d \frac{S_{base}}{M_{base}}$$
(2)

Figure 3 shows the voltage control block. In (3) and (5), Q and I_q are per unit values on the system base, and Q_{inv} and I_{qinv} are per unit values on the inverter rating base.



Figure 3 Voltage control

$$Q_{inv} = \frac{1}{1 + T_{Qf}s} Q \frac{S_{base}}{M_{base}}$$
(3)

$$V_{inv} = \frac{1}{1 + T_{Vf} s} V$$

$$I_{qinv} = \frac{1}{1 + T_{lf} s} I_q \frac{S_{base}}{M_{base}}$$
(4)
(5)

Figure 4 shows the PLL control block, and the voltages and currents in the
$$dq$$
 frame can be calculated using (6)–(9).



Figure 4 PLL block

$$I_d = I_x \cos \delta_{PLL} + I_y \sin \delta_{PLL} \tag{6}$$

$$I_q = -I_x \sin \delta_{PLL} + I_y \cos \delta_{PLL} \tag{7}$$

$$V_d = V_x \cos \delta_{PLL} + V_y \sin \delta_{PLL} \tag{8}$$

$$V_q = -V_x \sin \delta_{PLL} + V_y \cos \delta_{PLL} \tag{9}$$

The PQ priority algorithm can be used to determine the steady-state active current limit I_{dmaxSS} and reactive current limit I_{qmaxSS} , as shown in Figure 5.



Figure 5 PQ priority algorithm to determine the steady-state maximum active and reactive currents

The steady-state reactive current I_{qinv} can be limited by reducing the internal voltage magnitude E using the algorithm described in (10) and (11).

$$E_{\min} = \sqrt{(V_{inv} - I_{q\max SS} X_L)^2 + (I_{dinv} X_L)^2}$$
(10)

$$E_{\max} = \sqrt{(V_{inv} + I_{q\max SS} X_L)^2 + (I_{dinv} X_L)^2}$$
(11)

The steady-state active current I_{dinv} can be limited by using the control block described in Figure 6. (12) describes how to calculate δ_{max} .



Figure 6 Active current limiting block

$$\mathcal{S}_{\max} = \sin^{-1}(X_L I_{\max SS}) \tag{12}$$

Equation (13) and Figure 7 describe the transient current limiting function. When the transient current limiting is activated, the output current is limited algebraically by the network solution. Note that I_{maxF} should be set larger than I_{maxSS} .

$$I \angle \varphi = \frac{E_{VSM} \angle \delta_{VSM} - V \angle \delta_V}{R_e + jX_L}$$
(13)

$$E_{VSM} \angle \delta_{VSM} \xrightarrow{I < I_{maxF}} E \angle \delta_{E}$$

$$V \angle \delta_{V} + (R_{e} + jX_{L})I_{maxF} \angle \varphi \xrightarrow{I \ge I_{maxF}}$$

Figure 7 Transient current limiting function

[Symbol	Description	Unit	Example Value
	ωFlag	A flag to select whether to use the measured frequency from PLL as the input for the P-f droop.	NA	0
-	V _{drp} Flag	A flag to select whether to use Q or I_q as the input of the Q - V droop control.	NA	0
	QVFlag	A flag to determine whether Q_{ref} or V_{ref} should be used to interact with the plant controller.	NA	1
	PQFlag	A flag to determine whether P priority (PQFlag=1) or Q priority (PQFlag=0) should be selected.	NA	1
	FFlag	A flag to determine whether the power-frequency droop is enabled (FFlag=1) or disabled (FFlag=0).	NA	1
	ESFlag	A flag to determine if the model represents a battery source (ESFlag=1) or a non-battery source (ESFlag=0).	NA	1
	R_e	Inverter coupling resistance. (0 pu $\leq R_e \leq \frac{1}{4}X_L$)	pu	0
	X_L	Inverter coupling reactance. (0.04 pu $\leq X_L \leq 0.4$ pu)	pu	0.1
	m_q	<i>Q-V</i> droop gain. When $V_{drpflag}=1$, m_q represents a per unit virtual impedance.	pu	0.05
	k_{pv}	Proportional gain of the voltage controller	pu	0
	k_{iv}	Integral gain of the voltage controller	pu/s	5
	m_p	<i>P-f</i> droop gain	pu	0.02
	$\Delta \omega_{max}$	Upper limit of $\Delta \omega_m$	pu	0.05
	$\Delta \omega_{min}$	Lower limit of $\Delta \omega_m$	pu	-0.05
	k _{pPLL}	Proportional gain of PLL	pu	0.265
	<i>k</i> _{<i>i</i>PLL}	Integral gain of PLL	pu/s	2.65
	$\Delta \omega_{PLLmax}$	Upper limit of the PLL output	pu	0.2
	$\Delta \omega_{PLLmin}$	Lower limit of the PLL output	pu	-0.2
	T_p	Time constant of the low-pass filter in the VSM	s	0
	11	control block. $(I_p \ge 0)$		0.5
		Demaine	S	0.5
	D_1	Damping	pu	0
	D_2	I ransient damping	pu	100
	ω_D	Angular frequency of the washout block	pu	50
	ImaxSS	Steady-state current limit. ($I_{maxSS} \leq 0$ is treated as $1/X_L$) ($I_{maxSS} \leq 1/X_L$) ($I_{maxSS} \leq I_{maxF}$)	pu	1
	k _f	A factor to determine I_{qmax} (PQFlag=0) or I_{dmax} (PQFlag=1). If k_{f} =0, the software should reset it to be 1 and generate a warning message.	NA	0.9
	<i>k</i> _I	Integral gain for the active current limiting loop	pu/s	2
	ImaxF	Transient current limit	pu	1.5
	T_{pf}	Time constant of the low-pass filter for active power measurement	s	0.02 s
	TQf	Time constant of the low-pass filter for reactive power measurement	s	0.02 s
	T _{Vf}	Time constant of the low-pass filter for voltage measurement	s	0.02 s
	T _{If}	Time constant of the low-pass filter for current measurement	S	0.02 s
	Ke	Scalar on I_{dmax} for negative active steady-state current limitation (0 <= $K_e <= 1.0$)	NA	1
	ω_0	Rated angular frequency. Software tools typically have this value specified in the solution environment, so this will not be listed as an input parameter of the model	rad/s	376.99

Table 1 Model Main Circuit and Controller Parameters

References

Larsen EV, Delmerico RW, inventors; General Electric Co, assignee. Battery energy storage power conditioning system. United States patent US 5,798,633. 1998 Aug 25.



For more information, visit:

sites.google.com/view/unifi-consortium www.energy.gov/eere/solar/unifi-consortium